

i-SENSYS LBP3010	
Printer Engine	
Print speed	14 ppm mono (A4) ¹
Printing method	Monochrome laser beam printing
Print quality	Up to 2400 x 600 dpi with Automatic Image Refinement
Print resolution	Up to 600 x 600 dpi
Warm-up time	0 seconds from Standby Approx. 10 seconds or less from power on
First Page Out Time	Approx. 8.5 seconds or less
Duty cycle	Max 5,000 pages per month
Print margins	5 mm-top, bottom, left and right
Media handling	
Paper input (Standard)	150-sheet multi-purpose tray 1-sheet manual feed slot
Paper output	100-sheet face down
Media types	Plain paper, Heavy paper, Transparency, Label, Index card, Envelope
Media sizes	Multi-purpose tray: A4, B5, A5, Legal, Letter, Executive, 16K, Envelope DL, Envelope COM10, Envelope C5, Envelope Monarch, Custom sizes:76.2 to 215.9 mm wide and 127.0 to 355.6 mm long Manual feed slot: A4, B5, A5, Legal, Letter, Executive, 16K, Envelop
Media weights	Multi-purpose tray: 64 to 163 g/m ² Manual feed slot: 64 to 163 g/m ²
General features	
Power requirements	AC 220-240V (±10%), 50/60Hz (±2Hz)
Power consumption	Maximum: Approx. 880 W or less Active: Average approx. 280 W or less Standby: Average approx. 2 W or less Typical Electricity Consumption (TEC): 0.536 kWh/week
Noise level	Sound power ² : Active: 6.46 B or less Standby: Inaudible Sound pressure ² : Active: 50 dB(A) or less Standby: Inaudible
Dimensions (W x D x H)	372 mm x 250 mm x 197 mm
Weight	Approx. 5.94 kg
Operating environment	Temperature: 7.5 to 32.5°C (45.5 to 90.5°F) Humidity: 10 to 80% RH (no condensation)
Control panel	2 LED indicators, 1 operation key
Controller	

Memory	2 MB
Printer languages	Canon Advanced Printing Technology (CAPT)
Interface and connectivity	USB 2.0 Hi-Speed
Operating systems compatibility	Windows 2000/ Server 2003/ XP/ Vista Mac OS X Version 10.3.9-10.5.x ^{3 4} Linux ^{3 4}
Consumables	
All-in-One cartridges	Standard: Cartridge 712 (1,500 pages ⁵) ⁶
Accessories/ options	
Items	Network connectivity using AXIS 1650 Print Server
Standard disclaimer	All specifications subject to change without notice
Footnotes	
	[1] The print speed may drop depending on the printer driver settings, paper size, paper type and number of pages printed
	[2] Declared noise emission in accordance with ISO 9296
	[3] Web distribution only
	[4] English driver only
	[5] Based on ISO/IEC 19752 standard
	[6] Printer ships with 700 pages starter cartridge