



3-in-1 Wireless colour LED laser printer with touchscreen display

DCP-L3550CDW









PRINT

COPY

WIRELESS

brother.co.uk/dcp-l3550cdw

3-in-1 Wireless colour LED laser printer

The DCP-L3550CDW comes complete with time saving features including automatic 2-sided print, a large 250 sheet paper tray, and in-box toners printing up to 1,000 pages*. With wired and wireless connectivity for easy connectivity and the ability to print and scan from your mobile device, this machine is ready to use straight from the box.

DCP-L3550CDW



Key features:

- Fast print speeds of 18 pages per minute (ppm)
- Large paper capacity of 250 sheets
- Automatic 2-sided printing
- 50 sheet automatic document feeder (ADF)
- Easy to use 9.3cm colour touchscreen display
- Wired and wireless connectivity
- Up to 1,000 pages* in-box toners.

Designed with efficiency in mind

This robust desktop device is easy to use and simple to set up. The 50 sheet ADF allows you to scan multiple sheets at once and store to a location of your choice. Combine this with automatic 2-sided print and quick print options from both phone and tablet devices, this machine gives you the peace of mind required when running a business.

Add some colour to your business

Make an impact with colourful business documents. The DCP-L3550CDW offers up to 2,400dpi print quality, and uses LED laser technology to produce high quality professional prints. Not only does this machine print colour, but it also features a full colour touchscreen to access your favourite features quickly and easily.

Save time and money

These desktop devices are fast, reliable and great value. The built-in 250 sheet paper capacity allows you to keep working longer without having to replenish the paper tray. By using the high yield supplies, you won't have to spend time changing your toners as often, as well as achieving a competitive cost per page for both colour and mono printing. By boosting productivity, and reducing any down time, your office can run more smoothly.

Don't add to the office noise

You don't need any additional noise to distract you in the office. The DCP-L3550CDW has been engineered to print up to 18ppm at under 45dB - quieter than your daily office conversation.



General

Technology

Electrophotographic LED

Processor

Cortex-A9 800MHz Sub: ARM946 133MHz

Wired network

10Base-T/100Base-TX

Wireless network

IEEE 802.11b/g/n

Control panel

9.3cm colour touchscreen

Memory

512MB

Local interface

Hi-Speed USB 2.0

Mobile print

Print from your mobile devices to your Brother printer

Print

Print speed (A4)

18ppm colour and mono

Print speed 2-sided (A4)

6 sides per minute colour and mono.
Print on to both sides of the paper automatically

Resolution

2,400dpi (600 x 2,400)

Quiet mode

A mode to reduce the printing noise by reducing the print speed to 12ppm

First print out time

Less than 15.5 seconds from ready mode

Warm up time

Less than 28 seconds from sleep mode

Print languages

PCL6, BR-Script3 PDF Version 1.7, XPS Version 1.0

Embedded fonts (PCL)

73 scalable fonts, 12 bitmap fonts

Embedded fonts (Postscript)

66 scalable fonts

Embedded barcodes (PCL)

*Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN (EAN), ISBN (UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI

Printer functions

N-up printing³

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)

Poster printing⁴

Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages

Watermark printing⁴

Watermark your documents with predefined text or with your own user-defined messages

ID printing⁴

Add identification to your printed documents (date and time, short custom message or PC username)

Manual 2-sided print4

Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

Configurable shortcuts

Create up to 18 personaliased shortcuts for a quick and easy access to your regularly print, copy, scan and fax functions

Booklet printing⁴

Print documents in A5 booklet format using automatic or manual 2-sided print

Print profiles³

Store your favourite driver settings as profiles to easily recall them

Print text in black4

Converts all text in your documents to black when printed

Printer drivers

Windows®

Windows® 10 (32 and 64 bit editions) Windows® 8 (32 and 64 bit editions) Windows® 7 (32 and 64 bit editions) Windows® Server 2016 (32 and 64 bit editions)* Windows® Server 2012, 2012R2 and 2008R2* Windows® Server 2008 (32 and 64 bit editions)*

Macintosh⁵

macOS v10.11.6, 10.12.x, 10.13.x

Linux⁵

CUPS, LPD/LPRng (32 and 64 bit editions)

PostScript universal printer driver⁵

Driver for Windows® that enables you to print to any network or locally-connected Brother laser printer that supports PostScript

PCL driver⁵

Generic PCL XL driver

* Windows® Server supports network printing only

¹ Approx declared vield value in accordance with ISO/IEC 19798.

² Calculated with 80g/m² paper.

³ Windows® & Mac® only.

⁴ Windows® only. 5 Optional download.

⁶ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

⁷ Requires Brother Software.

⁸ Must be web connected.

Paper handling

Paper input

Standard tray - 250 sheets Manual feed slot - 1 sheet

ADF

50 sheets

Paper output

150 sheets face down (80g/m²)
1 sheet face-up (straight paper path)

Media type and weights standard tray

Plain and recycled paper (between 60 - 163g/m²)

Media sizes standard tray

A4, letter, A5, A5 (long edge), A6, executive

Media type and weights ADF

Plain and recycled paper (between 60 - 105g/m²)

Media sizes ADF

Width: 105 to 218 mm, Length: 148 to 357.6 mm

Media type and weights 2-sided print

Plain and recycled paper (between 60 - 163g/m²)

Media sizes 2-sided print A4

Envelope and label printing

Manual feed slot: support for 1 envelope / sheet

Media type and weights manual feed slot

Plain, recycled, bond, label, envelope paper (between 60 - 163g/m²)

Media sizes manual feed slot

Width: 76.2 to 216 mm, Length: 116 to 355.6 mm Envelope: COM -10, DL, C5,

Monarch

Mobile and web connectivity

Brother iPrint&Scan (Android)

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an Android device

Brother iPrint&Scan (iPad / iPhone / iPod)

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an iPad / iPhone / iPod Touch

Brother iPrint&Scan (Windows® Phone)

Print from and scan to a smart phone running the Windows® Phone operating system

Brother iPrint&Scan (Windows® 8,10 & RT)

Print from and scan to a Windows® 8,10 or Windows RT tablet

Google Cloud Print 2.0

Print most common file types from any Google Cloud Print enabled application

Apple AirPrint

Print from and scan to most common file types from any AirPrint enabled application

Brother print service plugin

Print from Android devices without a dedicated app

Mopria

Print most common file types from Mopria supported Android devices

Brother apps⁸

Print creative center, scan to mobile, scan to searchable PDF, enlarge tex copy, fax forward to cloud/e-mail, scan to PowerPoint, scan to Excel, scan to Word, easy scan to e-mail

Web connect⁸

Print from and scan to without using a PC on Box, Dropbox, Evernote, OneDrive, Google Drive™ OneNote

Copy

Copy speed (A4)

18 copies per minute colour and mono

First copy out time

Less than 17.5 seconds from ready mode colour and mono

Resolution

600 x 600dpi

Multi-copying/stack/sort

Makes up to 99 copies of each page / stacks and sorts

Enlargement/reduction ratio

Reduce or Increase document sizes from 25% to 400% in 1% increments

N in 1 copying

Allows the user to compress 2 or 4 pages on to a single A4 sheet

2 in 1 ID copying

Allows the user to copy both sides of an ID card to a single A4 sheet

Grey scale

256 shades of grey (8 bit)

Receipt copying

Produces clearer copies of receipts

Enlarge text copy⁸

Makes reading copied documents easier if the size of the text on the original document is small

¹ Approx declared vield value in accordance with ISO/IEC 19798.

² Calculated with 80g/m² paper.

³ Windows® & Mac® only.

⁴ Windows® only.

⁵ Optional download.

⁶ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

⁷ Requires Brother Software.

⁸ Must be web connected.

Scan

Scanner type

Contact image sensor

Colour and mono scanning

Yes

Scan speed mono

27 images per minute

Scan speed colour

21 images per minute

Scan resolution from scanner glass

1,200 x 2,400dpi

Interpolated scan resolution

19,200 x 19,200dpi

Scan resolution from ADF

600 x 600dpi

Colour depth

48 bit colour processing (input) 24 bit colour processing (output)

Grey Scale

16 bit colour processing (input) 8 bit colour processing (output)

Scanner functions

Scan to e-mail

Scan and share documents via e-mail server

Scan to OCR

Scan documents directly into your word processing application for instant editing

Scan to image

Scan into your preferred image editing software

Scan to file

Scan to a file on your computer

Scan to network folder

Scan documents to a nominated folder on your network without using a Windows PC

Scan to FTP

Scan documents directly to a FTP server

Scan profile³

Create up to 25 preset network, FTP profiles for an easy way to store multiple scan settings

Scan to SharePoint^{4&7}

Scan documents directly into SharePoint

Scan to searchable PDF

Scan documents to searchable PDF files

Auto deskew

Yes

Base colour removal

Yes

ID scan

Yes

1 to 2 scan

Yes

Scanner drivers

Windows®

TWAIN & WIA Windows® 10 (32 and 64 bit editions) Windows® 8 (32 and 64 bit editions) Windows® 7

(32 and 64 bit editions)

Macintosh⁵

TWAIN macOS v10.11.6, 10.12.x, 10.13.x

Linux⁵

SANE (32 and 64 bit editions)

Fleet management tools

Unattended installer4

Ability to centrally deploy and customise our drivers and software

MSI installer4

Modular installers that can be distributed through Active Directory®

BRAdmin Light^{4&5}

LAN/WAN management software

Embedded web server

Web based print management software embedded onto the device

Driver deployment wizard^{4 &5}

Easily create print drivers for hassle free deployment over your network

PrintSmart cost control

Monitor and control printing costs for all Brother and 3rd party devices

For more information on PrintSmart solutions visit: brother.co.uk

- 1 Approx declared yield value in accordance with ISO/IEC 19798.
- 2 Calculated with 80g/m² paper. 3 Windows® & Mac® only.
- 4 Windows® only.
- 5 Optional download
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.
- 7 Requires Brother Software.
- 8 Must be web connected.

Software

Brother iPrint&Scan (Windows & Mac)⁵

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from Windows, macOS or PC

Nuance® PaperPort 14 SE5

Document management & sharing program

Network and security

Wired network

10Base-T/100Base-TX

Wired network security

APOP, POP before SMTP, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP), SNMP v3 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos

Wireless network

IEEE 802.11b/g/n (infrastructure mode) IEEE 802.11g/n (Wi-Fi Direct)

Wireless network security

WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES)
*Wi-Fi Direct supports
WPA2-PSK (AES) only.APOP,
POP before SMTP,
SMTP-AUTH, SSL/TLS (IPPS,
HTTPS, SMTP, POP), SNMP v3
802.1x (LEAP, EAP-FAST,
PEAP, EAP-TLS, EAP-TTLS),
Kerberos

Wireless setup support

Wi-Fi Protected Setup (WPS)

Wireless applications

Vertical pairing

Wi-Fi Direct™

Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)

IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, SMTP Client, IPP/IPPS, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print/Scan), SNTP Client

IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, SMTP Client, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, SNTP Client, Web Services (Print/Scan)

IP filter

Restrict which network users can or cannot access the device over the network (IPv4 only)

E-mail notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

E-mail reports

Receive usage reports on a regular basis via e-mail

Setting lock

Secures access to the devices control panel by locking it

Secure Function Lock 3.0

Restrict access to individual or groups of users over a network. Can be used with PC user login names for up to 100 users

Secure print

Protect print jobs with a four digit release code required at the device in order for them to be printed

Supplies and accessories

In-box toner¹

1,000 pages BK/C/M/Y

Standard yield toner¹

1,000 pages BK/C/M/Y (TN-243)

High yield toner¹

3,000 pages BK 2,300 pages C/M/Y (TN-247)

Drum unit1

18,000 pages (1 page / job) (DR-243CL)

Belt unit1

Approx. 50,000 pages (2 page / job) (BU-223CL)

Waste toner box1

Approx. 50,000 pages (5 page / job) (WT-223CL)

- 1 Approx declared yield value in accordance with ISO/IEC 19798.
- 2 Calculated with 80g/m² paper.
- 3 Windows® & Mac® only.
- 4 Windows® only.
- 5 Optional download.
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.
- 7 Requires Brother Software.
- 8 Must be web connected.

Dimensions and weights

With carton (WxDxH) 589 x 523 x 568 mm 27.4kg

Without carton (WxDxH) 410 x 475 x 414 mm 23.2kg

Duty cycles

Recommended monthly

300 to 1,500 pages monthly print volume

Maximum monthly⁶

Up to 30,000 pages monthly print volume

Environment

Power consumption

Printing: 400W Ready: 80W Quiet mode: 280W Sleep: 9.7W Deep sleep: 1.2W Off: 0.04W

TEC value

0.9 kWh/Week

Sound pressure level

Printing: 45dB(A) Ready: 33dB(A) Quiet mode: 43dB(A)

Sound power

Printing: 5.92B(A) mono / 5.86B(A) colour Ready: 4.67B(A)

Quiet mode: 5.71B(A) mono /

5.73B(A) colour Deep sleep: inaudible

Power saving

This enables the printer to consume less energy when not in use

Toner saving

This reduces the toner usage and helps to reduce the total cost of printer ownership

Energy Star

GS mark

Yes

Eco mode

Yes

¹ Approx declared yield value in accordance with ISO/IEC 19798.

² Calculated with 80g/m² paper. 3 Windows® & Mac® only.

⁴ Windows® only.

⁵ Optional download.

⁶ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

⁷ Requires Brother Software.

⁸ Must be web connected.

















Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com

