



## SPECIFICATIONS

<b>Model Name</b>	X570-A PRO
<b>CPU Support</b>	Supports 2nd and 3rd Gen AMD Ryzen™ / Ryzen™ with Radeon™ Vega Graphics and 2nd Gen AMD Ryzen™ with Radeon™ Graphics Desktop Processors
<b>CPU Socket</b>	Socket AM4
<b>Chipset</b>	AMD® X570 Chipset
<b>Graphics</b>	2 x PCI-E 4.0 x16 slots
<b>Interface</b>	Supports 2-Way AMD® CrossFire™ Technology
<b>Display Interface</b>	HDMI - Requires Processor Graphics
<b>Memory Support</b>	4 DIMMs, Dual Channel DDR4-4400(OC)
<b>Expansion Slots</b>	3x PCIe 3.0 x1 slots
<b>Storage</b>	1 x Lightning M.2 slot (Gen4 x4) + 1 x Turbo M.2 slot (Gen3 x4) 6 x SATA 6Gb/s
<b>USB Ports</b>	2 x USB 3.2 (Gen2, A+C) + 8 x USB 3.2 (Gen1) + 6 x USB 2.0
<b>LAN</b>	Realtek® RTL8111H Gigabit LAN
<b>Audio</b>	8-Channel(7.1) HD Audio with Audio Boost 4

## FEATURES



### Frozr Heatsink Design

Designed with the patented fan and double ball bearings to provide best performance for enthusiast gamers and prosumers.



### Audio Boost 4

Isolated audio with a high quality audio processor for the most immersive gaming experience.



### Flash BIOS Button

Simply use a USB key to flash any BIOS within seconds, without installing a CPU, memory or graphics card.



### PCI-E Steel Armor

Protecting VGA cards against bending and EMI



### MULTI-GPU

Supports 2-way AMD CrossFire™ with optimal slot placement for the best airflow.



### Lightning Gen4 Solution

The latest Gen4 PCI-E and M.2 solution with up to 64GB/s bandwidth for maximum transfer speed.



### Core Boost


With premium layout and fully digital power design to support more cores and provide better performance.



### DDR4 Boost

Advanced technology to deliver pure data signals for the best gaming performance and stability.

## CONNECTIONS



1. Keyboard / Mouse
2. USB 3.2 Gen1 Type-A
3. LAN Port
4. HD Audio Connectors
5. Flash BIOS Button
6. USB 2.0 Ports
7. HDMI Port
8. USB 3.2 Gen2 Ports (Type-A + C)
9. USB 3.2 Gen1 Type-A Ports
10. Optical S/PDIF out